

ELEMEX SH11000 & SHT11500

Models			SH11000		SHT11500		
Type			R	LD	R	S	
Generator	Frequency (Hz)		50	60	50	60	
	Type		2-pole, Field Rotating Type				
	Voltage Regulation System		AVR				
	Phase		Single		Three		
	AC Output	Rated Power (kVA)	50Hz	8.5	-	10.0	-
			60Hz	-	9.5	-	11.5
		Maximum Power (kVA)	50Hz	10.0	-	11.5	-
			60Hz	-	11.0	-	13.0
	Rated Voltage (V)		220	120/240	220/380		
	Rated Power Factor (cosφ)		1.0		0.8		
Engine	Maker		HONDA				
	Model		GX630				
	Displacement (CC)		688				
	Net Power (kW)		15.1 (3,600rpm)				
	Ignition System		Transistor				
	Oil Alert System		YES				
	Starting System		Electric Starter				
Others	L x W x H (mm)		924 x 665 x 636 (804 with wheels)				
	Dry Weight (kg)	without wheel	158				
		with wheel	165				
	Fuel Tank Capacity (liters)		38				
	Sound Level [dB(A)/7m]	50Hz	74				
		60Hz					
	Continuous Operating Hours (hr)	50Hz	7.0	-	7.0	-	
		60Hz	-	6.2	-	6.2	
	Cooling System		Forced Air				
	Engine Oil Refill Capacity (liters)		1.8 (with replace a filter) / 1.5 (without replace a filter)				